


ILS or LOC RWY 20R
NASHVILLE INTL (BNA)

MISSED APPROACH: Climb to 1200 then climbing right turn to 4000 on heading 300° and on BNA VORTAC R-270 to BEVEE/BNA 22.4 DME/RADAR and hold.

The diagram shows a 4-qubit system. The first qubit is a control qubit, represented by a circle with a dot and the label A_4 . The second qubit is a target qubit, represented by a circle with a dot and the label A_4 . The third and fourth qubits are also represented by circles with dots. The control qubit is connected to the target qubit by a horizontal line. The target qubit is connected to the third and fourth qubits by a vertical line.

GND CON

CATEGORY	A	B	C	D
S-ILS 20R	778/40 200 (200-¾)			
S-LOC 20R	920/40 342 (400-¾)			
SIDESTEP 20C	960-1	372 (400-1)	960-1½ 372 (400-1½)	960-2 372 (400-2)
CIRCLING	1100-1 501 (600-1)	1120-1 521 (600-1)	1200-1¾ 601 (700-1¾)	1380-2½ 781 (800-2½)