

ILS or LOC RWY 27

MISSED APPROACH: Climb to 2900 direct CID VOR/DME and hold, continue climb-in-hold to 2900.


Diagram illustrating the Cedar Rapids VORTAC station (111.1 MHz, CID 25 NM, Chan 88) and its associated navigation aids. The station is located near Cedar Rapids, Iowa, with a distance of 114.1 miles (CID 25 NM) and a frequency of 111.1 MHz. The diagram shows the station's orientation, with a heading of 089° and a distance of 270° to WAVUM (087° (9.4)). The station is also shown with a 1009± distance to the (IAF) WAVUM INT I-RRU (7.1). The diagram includes a compass rose indicating the station's orientation, with a heading of 089° and a distance of 270° to WAVUM (087° (9.4)). The station is also shown with a 1009± distance to the (IAF) WAVUM INT I-RRU (7.1). The diagram includes a compass rose indicating the station's orientation, with a heading of 089° and a distance of 270° to WAVUM (087° (9.4)).

MIRA Rwy 13-31 1

MIRA Rwy 9-27 1

REIL Rwy 13

FAF to MAP 5.5 NM					
Knots	60	90	120	150	180
Min:Sec	5:30	3:40	2:45	2:12	1:50

2900 ↑ *LOC only	CID 	WAVUM INT I-RRU 7.1 Remain within 10 NM			
					
CATEGORY	A	B	C	D	
S-ILS 27#	1062/24 200 (200-½)				
S-LOC 27	1260/24 398 (400-½)	1260/35 398 (400-¾)			
CIRCLING	1280-1 411 (500-1)	1320-1 451 (500-1)	1560-2 691 (700-2)	1560-2¼ 691 (700-2¼)	